


Piccolo Alert PCIe

PCIe video capture card with four BNC connectors for up to 16 standard PAL/NTSC cameras



At a Glance

- 4x BNC connectors on the bracket, expandable to 16 with three [1203] VEB modules (sold separately)
- PCIe x1 bus
- Sixteen shared video decoders, 100/120 images per second (200/240 fields per second)
- Real-time acquisition from 4 cameras, fast switching between up to 16 cameras
- Independently-programmable frame rate and acquisition parameters for each video input

Benefits

Video input configurations

- Four cameras can be connected using the BNC connectors on the bracket: Acquisition at 30 (NTSC) or 25 (PAL) frames per second per camera
- Sixteen cameras can be connected using the BNC connectors on the bracket and three [1203] VEBs: Acquisition at 7.5 (NTSC) or 6.25 (PAL) frames per second per camera

Windows and Linux drivers available

Machine Vision for the General Manufacturing Industries

- Low cost image acquisition from industrial analog cameras for inspection machines

Life Sciences & Medical

- Standard and high-definition image acquisition for endoscopy applications
- Standard and high-definition image acquisition for dental applications

Microscopy

- High-definition image acquisition for offline inspection stations
- High-definition image acquisition for laboratory and measuring microscopes

ITS (Intelligent Transportation System) & Traffic management

- Video acquisition from multiple cameras

Specifications

Mechanical

Format	Standard profile, half length, 1-lane PCI Express card
Dimensions	L 167.65 mm x H 106.65 mm L 6.6 in x H 4.38 in

Host bus

Standard	PCI Express 1.0
Link width	1 lane
Link speed	2.5 GT/s (PCIe 1.0)
DMA	32-bit
Peak delivery bandwidth	256 MB/s
Effective (sustained) delivery bandwidth	180 MB/s (Host PC motherboard dependent)
Power consumption	Max. 9.5 W (2.9 A @ +3.3 V)

Camera / video inputs

Interface standard(s)	NTSC-M, PAL-B/G, RS-170, CCIR
Connectors	<ul style="list-style-type: none">• VIDEO 1 to VIDEO 4: BNC female connectors on the bracket for composite video inputs• VEB LINK 0 to VEB LINK 3: 10-pin shrouded header connectors on the PCB for VEB modules
Termination resistor	Selectable using switches on the bracket
Native resolution	Square pixels, broadcast and custom resolutions
Frame rate	<ul style="list-style-type: none">• Up to 25/30 images per second, 50/60 fields per second per input• Total 100/120 images per second with up to 16 cameras
Number of cameras	16
Number of cameras (at full frame rate)	4

Video delivery

Raw video format(s)	<ul style="list-style-type: none">• Packed RGB color formats: RGB15, RGB16, RGB24, RGB32• Planar RGB color formats: RGB24PL• Packed YUV color formats: YUV411, YUV422, YUV444• Planar YUV color formats: YUV411PL, YUV422PL, YUV444PL, YUV411PL, YUV422PL• Monochrome formats: Y8
Deliverable video resolution (SD)	Frame, field, CIF, QCIF and custom image formats

Area-scan camera control

Trigger	<ul style="list-style-type: none">• Hardware trigger for up to four cameras• With configurable noise removal filter and optional delay
Strobe	<ul style="list-style-type: none">• Hardware strobe signal for up to four cameras• With programmable position and duration

General Purpose Inputs and Outputs

Number of lines	9 I/O lines: <ul style="list-style-type: none">• 4 contact closure inputs (IN)• 5 solid-state relay outputs (OUT)
-----------------	--

Connectors	I/O: 20-pin dual-row 0.1" shrouded header on the PCB
Usage	General purpose IO
Electrical specifications	<ul style="list-style-type: none"> • IN: Polarity-free inputs, compatible with TTL, 12V and 24V signals, opto-couplers, relays and switches • OUT: Opto-isolated potential-free and polarity-free solid-state outputs, compatible with signals up to 30V, with 4 μs fall time, isolated up to 500V
Watchdog	Yes

Software

Host PC Operating System	<ul style="list-style-type: none"> • Microsoft Windows 10, 8.1, 7 for x86 (32-bit) and x86-64 (64-bit) processor architectures • Linux for x86 (32-bit) and x86-64 (64-bit) processor architectures <p>Refer to release notes for details</p>
APIs	<ul style="list-style-type: none"> • MultiCam 32- and 64-bit binary libraries (Windows and Linux), for ISO-compliant C/C++ compilers • DirectShow 32- and 64-bit filters (Windows only), for Microsoft Visual C++ compilers

Environmental conditions

Operating ambient air temperature	0 to +50 °C / +32 to +122 °F
Operating ambient air humidity	10 to 90% RH non-condensing
Storage ambient air temperature	-20 to +70 °C/ -4 to +158 °F
Storage ambient air humidity	10% to 90% RH non-condensing

Certifications

Electromagnetic - EMC standards	<ul style="list-style-type: none"> • European Council EMC Directive 2004/108/EC • United States FCC rule 47 CFR 15
EMC - Emission	<ul style="list-style-type: none"> • EN 55022:2010 Class B • FCC 47 Part 15 Class B
EMC - Immunity	<ul style="list-style-type: none"> • EN 55024:2010 Class B • EN 61000-4-2 • EN 61000-4-3 • EN 61000-4-5 • EN 61000-4-6
KC Certification	Korean Radio Waves Act, Article 58-2, Clause 3
Flammability	PCB compliant with UL 94 V-0
RoHS	European Union Directive 2015/863 (ROHS3)
REACH	European Union Regulation 1907/2006
WEEE	Must be disposed of separately from normal household waste and must be recycled according to local regulations

Ordering Information

Product code - Description	<ul style="list-style-type: none"> • 1641 - Picolo Alert PCIe
----------------------------	--



EMEA

Euresys SA

Liège Science Park - Rue du Bois Saint-Jean, 20
4102 Seraing - Belgium

Phone: +32 4 367 72 88

Email: sales.europe@euresys.com

EMEA

Sensor to Image GmbH

Lechtorstrasse 20 -
86956 Schongau - Germany

Phone: +49 8861 2369 0

Email: sales.europe@euresys.com

AMERICA

Euresys Inc.

27132-A Paseo Espada - Suite 421
San Juan Capistrano, CA 92675 - United States

Phone: +1 949 743 0612

Email: sales.americas@euresys.com

ASIA

Euresys Pte. Ltd.

750A Chai Chee Road - #07-15 ESR BizPark @ Chai Chee
Singapore 469001 - Singapore

Phone: +65 6445 4800

Email: sales.asia@euresys.com

CHINA

Euresys Shanghai Liaison Office

Unit 802, Tower B, Greenland The Center - No.500 Yunjin Road, Xuhui District
200232 Shanghai - China

Euresys 上海联络处

上海市徐汇区云锦路500号绿地汇中心B座802室
200232

Phone: +86 21 33686220

Email: sales.china@euresys.com

JAPAN

Euresys Japan K.K.

Expert Office Shinyokohama - Nisso Dai 18 Building, Shinyokohama 3-7-18, Kohoku
Yokohama 222-0033 - Japan

〒222-0033

神奈川県横浜市港北区新横浜3-7-18 日総第18ビル エキスパートオフィス新横浜

Phone: +81 45 594 7259

Email: sales.japan@euresys.com

More at www.euresys.com

