Data Sheet



VIAVI

T-BERD/MTS-6000A and -8000 Platforms

OSA-110M/110H/110R Compact Full-Band OSAs

Test xWDM Networks with a Compact, Full-Band Optical Spectrum Analyzer

The OSA-110 Series is the next generation of compact VIAVI Solutions[™] optical spectrum analyzer (OSA) modules with unmatched size, weight, price, and performance, which make it ideal for field use. Housed inside the T-BERD/MTS-6000A series platform, it offers the smallest full-band OSA solution on the market.

The OSA-110 Series is suitable for all optical coarse wavelength division multiplexing (CWDM) and dense wavelength-division multiplexing (DWDM) networks down to 33 GHz channel spacing. In addition to standard features provided by the OSA-110M, the OSA-110H integrates a high-power measurement capability, making it the ideal tool for cable operators. The OSA-110R includes the well-known VIAVI in-band measurement technique to measure the true OSNR in ROADM-based networks and in 40 G systems with overlapping spectra.

The combination of high optical resolution with full-band measurement capability makes the OSA-110 Series ideal for testing power, wavelength, OSNR, and drift during provisioning, maintenance, and upgrades of WDM systems.

Platform Compatibility

T-BERD/MTS-6000A



Modular platform for fiber and multiple-services testing

T-BERD/MTS-8000 (V2)



Scalable platform for multiple-layer and multiple-protocol testing

Key Benefits

- Improved field operation with the smallest and lightest full-band OSA available
- Suitable for all CWDM and DWDM applications down to 33 GHz channel spacing
- One-touch test with automatic pass/fail analysis
- Future-proof signal analysis for 40/100 G testing and new modulation formats
- In-band OSNR measurements in ROADM and 40 G networks

Key Features

- Full-band measurement range from 1250 to 1650 nm
- Built-in wavelength calibration guarantees ±0.05 nm wavelength accuracy
- High-power version accommodates power levels up to +30 dBm
- In-band version to measure true OSNR in ROADM and 40 G networks

Applications

- Deploying and maintaining DWDM metro and core networks
- Installing and maintaining CWDM systems in CATV, access, and mobile backhaul
- Verifying high-speed 40/100 G interfaces
- Provisioning and troubleshooting ROADM networks

Specifications¹

| Specifications ¹ | | | | | |
|--|---|--|--|--|--|
| Modes | | | | | |
| Analysis | WDM, drift, DFB, OO-OSNR, inband OSNR (OSA-110R only) | | | | |
| Display | Graph, WDM table, graph and table | | | | |
| WDM Measurement | | | | | |
| Channel spacing | 33 to 200 GHz, CWDM | | | | |
| Max no. of channels | 256 | | | | |
| Data signals | No data rate limit, all data rates supported | | | | |
| Modulation formats | All formats supported | | | | |
| Spectral Measurement | 1 | | | | |
| Wavelength range | 1250 to 1650 nm | | | | |
| Abs. wavelength accuracy ^{2, 3} | ± 0.05 nm | | | | |
| Wavelength reference | Internal | | | | |
| Wavelength repeatability ^{2, 4} | ±0.01 nm | | | | |
| Resolution bandwidth (FWHM) ² | 0.1 nm | | | | |
| Readout resolution | 0.001 nm | | | | |
| Scanning time (including WDM | analysis) | | | | |
| Full band | <5 s | | | | |
| C-band | 1 s | | | | |
| Measurement samples | 111,000 | | | | |
| Power Measurement | | | | | |
| Absolute accuracy ^{2, 8} | ±0.6 dB | | | | |
| Readout resolution | 0.01 dB | | | | |
| Flatness ^{2, 8} | ±0.3 dB | | | | |
| PDL ² | ±0.2 dB | | | | |
| Power Measurement (OSA-110 | M/OSA-110R) | | | | |
| Dynamic range per channel ⁵ | -60 to +15 dBm | | | | |
| Total safe power | +23 dBm | | | | |
| Linearity ^{2, 6} | ±0.1 dB | | | | |
| Power Measurement (OSA-110 | H) | | | | |
| Dynamic range per channel ⁵ | -50 to +25 dBm | | | | |
| Total safe power | +30 dBm | | | | |
| Linearity ^{2, 7} | ±0.1 dB | | | | |
| Optical Measurement | | | | | |
| Optical rejection ratio (ORR) ² | | | | | |
| At \pm 0.2 nm (for 50 GHz channel spacing) | 35 dBc | | | | |
| At ± 0.4 nm (for 100 GHz channel spacing) | 40 dBc | | | | |
| OSNR accuracy ⁹ | ±0.6 dB | | | | |
| OSNR range | >30 dB | | | | |
| In-Band OSNR (OSA-110R) | | | | | |
| I-OSNR dynamic range | up to >25 dB | | | | |
| PMD tolerance ¹⁰ | up to 10 ps | | | | |
| Data signals ¹¹ | up to 40 G | | | | |

| General | | | | | |
|----------------------|---|--|--|--|--|
| Optical port | universal SM-PC, universal SM-APC | | | | |
| Connectors | FC, SC, ST, LC, DIN | | | | |
| ORL | >35 dB | | | | |
| Size (module) | 122 x 235 x 26 mm (4.8 x 9.3 x 1.0 in) | | | | |
| Weight (module) | 0.6 kg (1.3 lb) | | | | |
| Temperature | | | | | |
| Operating Storage | +5 to +40°C (41 to 104°F) -20 to +60°C (-4 to 140°F) | | | | |
| Relative humidity | 0 to 95% noncondensing | | | | |

- 1. Unless otherwise specified, all specifications are based on a temperature of 23°C \pm 2°C with an FC/PC connector, after warm-up.
- 2. Typical for 1520 to 1565 nm at 18 to 23°C.
- 3. Recommended period for recalibration is 2 years.
- 4. In 5 consecutive scans.
- 5. From 1520 nm to 1610 nm.
- 6. Signal power from -45 dBm to +10 dBm.
- 7. Signal power from -35 dBm to +20 dBm.
- 8. At -10 dBm including PDL.
- 9. Typical value with equal channel power for OSNR up to 25 dB and signal >-30 dBm for OSA-110M/R and >-20 dBm for OSA-110H.
- 10. For data rates up to 10 G.
- 11. Except for pol-mux and polarization scrambled signals.

Ordering Information

| Description | Part Number | | | | | |
|--|-------------|--|--|--|--|--|
| OSA Modules | | | | | | |
| OSA-110M, PC version | 2304/91.02 | | | | | |
| OSA-110M, APC version | 2304/91.12 | | | | | |
| OSA-110H, high-power PC version | 2304/91.03 | | | | | |
| OSA-110H, high-power APC version | 2304/91.13 | | | | | |
| OSA-110R, in-band OSNR PC version | 2304/91.04 | | | | | |
| OSA-110R, in-band OSNR APC version | 2304/91.14 | | | | | |
| Application Software for Report Generation | | | | | | |
| FiberTrace2 reporting software | EOFS100 | | | | | |
| FiberCable 2 reporting software | EOFS200 | | | | | |

VIAVI Care Support Plans

Increase your productivity for up to 5 years with optional VIAVI Care Support Plans:

- Maximize your time with on-demand training, priority technical application support and rapid service.
- Maintain your equipment for peak performance at a low, predictable cost.

For more Information: go to viavisolutions.com/viavicareplan

Features *5-year plans only

| Plan | Objective | Technical Assistance | Factory Repair | Priority Service | Self-paced Training | 5 Year Battery and Bag Coverage | Factory Calibration | Accessory Coverage | Express Loaner |
|------------|--|-------------------------|-------------------|---------------------|------------------------|---------------------------------------|------------------------|-----------------------|-------------------|
| BronzeCare | Technician Efficiency | Premium | ✓ | ✓ | ✓ | | | | |
| SilverCare | Maintenance & Measurement Accuracy | Premium | ✓ | √ | ✓ | √ * | ✓ | | |
| MaxCare | High Availability | Premium | ✓ | √ | ✓ | √ * | √ | √ | √ |



Contact Us

+1 844 GO VIAVI (+1 844 468 4284)

To reach the VIAVI office nearest you, visit viavisolutions.com/contacts.

© 2020 VIAVI Solutions, Inc. Product specifications and descriptions in this document are subject to change without notice. osa110-ds-fop-nse-ae 30173378 904 0120