

FMC-RCP-10G

Datasheet Revision: 1.0



Applications

- · 40G Ethernet · High-Speed Communications

One Year Technical Support

Board Features . 1 or 2 ARINC 801 Connectors

Summary

The FMC-RCP-10G is an FMC I/O Module with up to four 10Gb/s Optical transceiver channels. Based on the FMC Standard (VITA 57.1) but with modified profile and increased front IO area to

accommodate the optical transceivers. Suitable for use in harsh environments with LuxCis optical connectors and full speed operation over the industrial temperature range.

Deliverables

Input/Output Interfaces

FMC-RCP-10G Board 2x Optical Links - 850nm (2 Tx & 2 x) One Year Warranty





FMC Pinout available in User Manual

Environmental Specification

Temperature Ranges

| Cooling Option | Operating Temperatures | | Storage Temperatures | |
|-------------------|------------------------|------|----------------------|-------|
| | Min | Max | Min | Max |
| AC1 | -40°C | 70°C | -55°C | 100°C |
| CC1 | -40°C | 70°C | -55°C | 100°C |

Operating Humidity: Up to 95% (non-condensing)

EMC Standards

FCC 47CFR Part 2 EN55022:2010 Equipment ClassB

Conformal Coating Options Acrylic or Polyurethane

Contact sales for specification of coatings.

Order Code: FMC-RCP-10G/l(f0)(c)(a)

| Option | Code | Description of Options |
|---------------------|------|---|
| Lanes | - 1 | 2 = 2Tx + 2 Rx Lanes (one RCP Module), 4 = 4Tx + 4 Rx Lanes (two RCP Module) |
| Referency Frequency | 10 | blank = 156.250MHz, /xxx.yyy (specify frequency in MHz) |
| Cooling | c | blank = air cooled industrial, ICC1 = conduction cooled industrial |
| Conformal Coating | a | blank = no conformal coating. A = Acrylic, D = Bobuverbone. |

Address: 160 Dundee Street, Suite 4A. Edinburgh, EH11 1DQ, UK Telephone: +44 131 558 2600 Fax: +44 131 558 2700 email: sales@alpha-data.com http://www.alpha-data.com

website:

Address: 611 Corporate Circle Suite H Golden, CO 80401 Telephone: (303) 954 8768
Fax: (866) 820 9956 - toll free email: sales@alpha-data.com website: http://www.alpha-data.com